

## Amended Specification: Clean Version

### **Method for the operation of a flow measurement system**

5 This application is the national phase filing of  
International Application No. PCT/EP2005/000396 filed  
on January 17, 2005 published as WO2005/069017 which  
designated at least one country other than the United  
States of America ("the PCT Application") and the PCT  
10 Application claims the priority of German Application  
No. 10 2004 002 546.0 filed on January 17, 2004 ("the  
German Application") and the contents of the PCT  
Application and the German Application are relied upon  
and incorporated herein by reference in their entirety,  
15 and the benefit of priority under 35 U.S.C. 119 is  
hereby claimed.

#### Field of the Invention

The method described herein relates to magnetic-  
20 inductive flow measurement devices.

#### Description of the Prior Art

The physical effect which is used in magnetic-inductive  
flow measurement devices to measure the flow rate is  
the induction law. When an electrically conductive  
25 measurement substance is passed through a magnetic  
field B, then an electrical field E is produced in the  
measurement substance at right angles to the flow  
direction v and to the magnetic field correction.

30 Power must be supplied to the measurement system in  
order to produce a magnetic field B. As is known, this  
power is always constant.

However, this does not always result in optimum signal  
35 generation.

#### Summary of the Invention

In the present invention an instantaneous signal-to-

noise ratio determination is carried out automatically in the signal processing of the flow measurement device during the measurement phase, and the power supplied to the measurement system is adapted as a function of the  
5 result. A power supply which is optimally matched to the requirement is thus provided completely automatically.

A further advantageous refinement provides that the  
10 power which is supplied is adapted in inverse proportion to the signal-to-noise ratio. This means that the higher the signal voltage in comparison to the noise, the less is the power that is required. However, the smaller the signal voltage with respect to the  
15 noise voltage, the greater is the power which should be supplied to the measurement system.

A further factor is that the instantaneous value of the signal-to-noise ratio and/or of the power which is  
20 supplied or a variable which is proportional to them or it is indicated. This allows the instantaneous measurement profile to be observed.

A further advantageous refinement provides for the  
25 variable power supply to be achieved by adaptation of the magnetic field strength. This automatically becomes greater, the greater the ratio of the noise to the measurement signal.

30 A further advantageous refinement provides that if the noise voltages are high, a visual and/or audible warning is generated. This warning makes the operator aware of the high noise voltages since excessive noise may indicate a fault.

35 A final advantageous refinement provides that if the flow rate is zero or virtually zero, the power supply is automatically switched off, or is temporarily

switched off.

#### Brief Description of the Drawings

5 The only drawing figure shows a graph that illustrates the energy that can be saved by using the present invention and the constant power that is supplied in prior art flow measurement systems.

#### Detailed Description

10

The method of the invention provides an intelligent measurement system which, after evaluation of the ratio of the signal voltage to the noise voltage, automatically determines the required optimum magnitude  
15 of the signal voltage via the magnitude of the magnetic field, and thus the power required for the measurement system. This is an automatic determination and the required power is adjusted for the respective measurement task.

20

The power requirement for the measurement parts can likewise be reduced to the minimum power consumption when the flow rate is zero.

25 This measurement system allows an optimized power supply to be achieved for all measurement tasks, independently of the respective excitation frequency. Considerable energy cost savings can thus be achieved, while at the same time lengthening the life of the  
30 measurement system. The life of the flow measurement device can be lengthened because the maximum amount of power is not always used, as in the normal case.

35 The illustrated curve (thick line with the label "invention") shows the energy which can be saved for different requirements for the measurement system, in terms of the noise voltage in different measurement applications. In contrast to this, the graph shows that

100% of the power is always supplied in the prior art.  
In the case of the present invention, this is done only  
when the signal-to-noise ratio is extremely poor.  
Otherwise, the power supply always remains well below  
5 that according to the prior art. This power adaptation  
is carried out automatically in the described manner,  
according to the invention.

At the same time, it is possible to use this  
10 measurement system to carry out a diagnosis of the  
measurement signal voltage and to emit a warning to the  
operator of the measurement station when the noise  
voltages are very high.

